

Print Document Content

This chapter covers the following topics:

- Description
 - Procedure
 - Batch Example
-

Description

Program

B07111

Function

Print document content by cabinet, name, folder and date.

Online Input Screen

4:32 PM	* * * C O N - N E C T 3 * * *		14.Feb.94
Cabinet LS	Print Document Content		B07111
From Cabinet	_____		
Document	_____	to Document	_____
Folder	_____	to Folder	_____
Date	1.Jan.86	to Date	14.Feb.94
Mark to print			
	Banner	—	
	Attached Notes	—	
	Address Lists	—	
	Pagebreaks	—	
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---			
Menu Quit			
Complete the information above and press ENTER to continue			

Utility Parameters

Parameter	Format	Description
From Cabinet	A8	
From Document	A32	Optional
To Document	A32	Optional
From Folder	A15	Optional
To Folder	A15	Optional
From Date	A11	Default: 1.Jan.86
To Date	A11	Default: current date
Print Banner	A1	Optional
Print Notes	A1	Optional
Print Addressees	A1	Optional
Pagebreaks	A1	Optional

Procedure

Users can only print documents in their own cabinets. However, they can also print documents in cabinets where they have been authorized to do so (i.e. member of a shared cabinet or authorized with the SHARE command). Documents contained in cabinet SYSCNT and in public cabinets can be printed by anyone.

The Pagebreaks parameter refers to the page breaks between banner, notes, addressees and the text of the document. By default this parameter is blank and a page break will not occur between these items - instead, a delimiting line is generated. There is always a page break at the start of a new document.

If you want to print items from a bulletin board, enter SYSCNTB for the cabinet-name and a bulletin board in the Folder parameter.

Batch Example

Print all documents from the folder Work of the cabinet Con-nect, including banner, notes and addressees. This would be coded as follows:

```
LOGON SYSCNT2B
MENU
B07111 Con-nect,*,,WORK,,,,X,X,X
FIN
```